

配件

串口连接配件	
串口连接盒和连接线的使用图.....	94
8口RS-232连接盒.....	95
8口RS-232连接线.....	95
2口连接线.....	96
4口连接线.....	96
8针RJ45转DB9/DB25连接线.....	96
10针RJ45转DB9/DB25连接线.....	97
布线工具.....	97
电源配件	
电源线.....	98
电源适配器.....	98
宽温电源适配器.....	101
电源适配器.....	101
光纤配件	
光纤配件.....	102
金属帽102	
连接器103	
安装工具104	

A

配件



串口连接配件

： 串口连接盒和连接线的使用图

串口卡型号	连接盒						连接线																
	8口						8口							4口				2口					
	OPT8-M9	OPT8-RJ45	OPT8A/B/S	OPT8-M9+	OPT8A+/B+/S+	OPT8-RJ45+	CBL-M68M25x8-100 (OPT8C+)	CBL-M68M9x8-100 (OPT8D+)	CBL-M62M25x8-100 (OPT8C)	CBL-M62M9x8-100 (OPT8D)	CBL-M78M25x8-100	CBL-M78M9x8-100	CBL-M44M9x4-50	CBL-M44M9x4-50(POS)	CBL-M44M25x4-50	CBL-M37M9x4-30 (OPT4C)	CBL-M37M9x4-30 (OPT4D)	CBL-F40M9x4-50	CBL-F40M25x4-50	CBL-M25M9x2-50	CBL-F20M9x2-50	CBL-F20M25x2-50	
C218Turbo 系列	✓	✓	✓	-	-	-	-	-	✓	✓	-	-	-	-	-	-	-	-	-	-	-	-	-
C104H 系列	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	✓	-	-	-	-	-	-	-
CP-114 系列	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	✓	-	-	-	-	-	-	-
CI-134 系列	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	✓	-	-	-	-	-	-	-
CP-118U	✓	✓	✓	-	-	-	-	-	✓	✓	-	-	-	-	-	-	-	-	-	-	-	-	-
CP-138U	✓	✓	✓	-	-	-	-	-	✓	✓	-	-	-	-	-	-	-	-	-	-	-	-	-
CP-168U	✓	✓	✓	-	-	-	-	-	✓	✓	-	-	-	-	-	-	-	-	-	-	-	-	-
C168H 系列	✓	✓	✓	-	-	-	-	-	✓	✓	-	-	-	-	-	-	-	-	-	-	-	-	-
CP-104UL	-	-	-	-	-	-	-	-	-	-	-	✓	-	✓	-	-	-	-	-	-	-	-	-
CP-134U 系列	-	-	-	-	-	-	-	-	-	-	-	✓	-	✓	-	-	-	-	-	-	-	-	-
CP-114UL	-	-	-	-	-	-	-	-	-	-	-	✓	-	✓	-	-	-	-	-	-	-	-	-
CP-114UL-I	-	-	-	-	-	-	-	-	-	-	-	✓	-	✓	-	-	-	-	-	-	-	-	-
CP-104EL-A	-	-	-	-	-	-	-	-	-	-	-	✓	-	✓	-	-	-	-	-	-	-	-	-
CP-114EL	-	-	-	-	-	-	-	-	-	-	-	✓	-	✓	-	-	-	-	-	-	-	-	-
CP-114EL-I	-	-	-	-	-	-	-	-	-	-	-	✓	-	✓	-	-	-	-	-	-	-	-	-
CP-112UL	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	-	-	-
CP-112UL-I	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	-	-	-
CP-132UL 系列	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	-	-	-
CP-102UL	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	-	-	-
CP-102EL	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	-	-	-
CP-132EL	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	-	-	-
CP-132EL-I	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	-	-	-
CP-118EL-A	-	-	-	✓	✓	✓	✓	✓	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
CP-168EL-A	-	-	-	✓	✓	✓	✓	✓	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
CP-118U-I	-	-	-	-	-	-	-	-	-	✓	✓	-	-	-	-	-	-	-	-	-	-	-	-
CP-138U-I	-	-	-	-	-	-	-	-	-	✓	✓	-	-	-	-	-	-	-	-	-	-	-	-
POS-104UL	-	-	-	-	-	-	-	-	-	-	-	-	✓	-	-	-	-	-	-	-	-	-	-
CA-108	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	✓	-	-	-	-
CB-108	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	✓	-	-	-	-
CA-114	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	✓	-	-	-	-
CB-114	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	✓	-	-	-	-
CA-134I	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	✓	-	-	-	-
CB-134I	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	✓	-	-	-	-
CA-104	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	✓	-	-	-	-
CA-132	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	✓	-
CA-132I	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	✓	✓	-

A

配件 > 串口连接配件

配件名

配件名	OPT8-M9	OPT8-RJ45	OPT8A/S	OPT8B
配件图像				
针脚分配				
主板端	DB62 针式 x 1			
设备端	DB9 针式 x 8	8-针RJ45 x 8	DB25 孔式 x 8	DB25针式 x 8
LED	TxD, RxD indicators for each device-side port	-	TxD, RxD indicators for each device-side port	-
速率	-	-	50 bps ~ 921.6 Kbps	-
尺寸	90 x 111 x 27.5 mm (3.5 x 4.3 x 1 in)	152.8 x 32.8 x 32 mm (6 x 1.29 x 1.25 in)	247 x 108 x 35 mm (9.7 x 4.3 x 1.4 in)	-
保护	-	-	25 KV ESD, 2 KV EFT surge protection (OPT8S only)	-
接口电缆	DB62 male ~ DB62 female 150 cm connection cable for connecting to the serial board	-	DB62 male to DB62 male 150 cm connection cable for connecting to the serial board	-
相关产品	详情请看A-2			

配件名	OPT8-M9+	OPT8-RJ45+	OPT8A+/S+	OPT8B+
配件图像				
针脚分配				
主板端	VHDCI 68 x 1			
设备端	DB9 针式 x 8	8-针 RJ45 x 8	DB25 孔式 x 8	DB25 针式 x 8
LED	TxD, RxD indicators for each device-side port	-	TxD, RxD indicators for each device-side port	-
速率	-	-	50 bps ~ 921.6 Kbps	-
尺寸	90 x 111 x 27.5 mm (3.5 x 4.3 x 1 in)	152.8 x 32.8 x 32 mm (6 x 1.29 x 1.25 in)	247 x 108 x 35 mm (9.7 x 4.3 x 1.4 in)	-
保护	-	-	25 KV ESD, 2 KV EFT surge protection (OPT8S only)	-
接口电缆	DB68 male to DB62 female 150 cm connection cable for connecting to the serial board	-	DB68 male ~ DB62 male 150 cm connection cable for the connecting to the serial board	-
相关产品	详情请看A-2			

8口RS-232连接线

配件名	CBL-M62M25x8-100 (OPT8C)	CBL-M62M9x8-100 (OPT8D)	CBL-M68M25x8-100 (OPT8C+)	CBL-M68M9x8-100 (OPT8D+)	CBL-M78M25x8-100	CBL-M78M9x8-100
配件图像						
针脚分配						
主板端	DB62 male x 1		VHDCI 68 x 1		DB78 male x 1	
设备端	DB25 male x 8	DB9 male x 8	DB25 male x 8	DB9 male x 8	DB25 male x 8	DB9 male x 8
电缆长度	100 cm					
相关产品	详情请看A-2h					

A

配件 > 串口连接配件

2口连接线

配件名	CBL-M25M9x2-50																		
配件图像																			
针脚分配	<table border="1"> <thead> <tr> <th>PIN</th> <th>RS-232</th> </tr> </thead> <tbody> <tr><td>1</td><td>DCD</td></tr> <tr><td>2</td><td>RxD</td></tr> <tr><td>3</td><td>TxD</td></tr> <tr><td>4</td><td>DTR</td></tr> <tr><td>5</td><td>GND</td></tr> <tr><td>6</td><td>DSR</td></tr> <tr><td>7</td><td>RTS</td></tr> <tr><td>8</td><td>CTS</td></tr> </tbody> </table>	PIN	RS-232	1	DCD	2	RxD	3	TxD	4	DTR	5	GND	6	DSR	7	RTS	8	CTS
PIN	RS-232																		
1	DCD																		
2	RxD																		
3	TxD																		
4	DTR																		
5	GND																		
6	DSR																		
7	RTS																		
8	CTS																		
描述	DB25 male to DB9 male x 2																		
电缆长度	50 cm																		
相关产品	详情请看A-2																		

4口连接线

配件名	CBL-M44M9x4-50	CBL-M44M25x4-50																																																																																																				
配件图像																																																																																																						
针脚分配	<table border="1"> <thead> <tr> <th>PIN</th> <th>RS-232</th> <th>RS-422</th> <th>RS-485-4w</th> <th>RS-485-2w</th> </tr> </thead> <tbody> <tr><td>1</td><td>DCD</td><td>TxD-(A)</td><td>TxD-(A)</td><td>-</td></tr> <tr><td>2</td><td>RxD</td><td>TxD+(B)</td><td>TxD+(B)</td><td>-</td></tr> <tr><td>3</td><td>TxD</td><td>RxD+(B)</td><td>RxD+(B)</td><td>Data+(B)</td></tr> <tr><td>4</td><td>DTR</td><td>RxD-(A)</td><td>RxD-(A)</td><td>Data-(A)</td></tr> <tr><td>5</td><td>GND</td><td>GND</td><td>GND</td><td>GND</td></tr> <tr><td>6</td><td>DSR</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>7</td><td>RTS</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>8</td><td>CTS</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>9</td><td>-</td><td>-</td><td>-</td><td>-</td></tr> </tbody> </table>	PIN	RS-232	RS-422	RS-485-4w	RS-485-2w	1	DCD	TxD-(A)	TxD-(A)	-	2	RxD	TxD+(B)	TxD+(B)	-	3	TxD	RxD+(B)	RxD+(B)	Data+(B)	4	DTR	RxD-(A)	RxD-(A)	Data-(A)	5	GND	GND	GND	GND	6	DSR	-	-	-	7	RTS	-	-	-	8	CTS	-	-	-	9	-	-	-	-	<table border="1"> <thead> <tr> <th>PIN</th> <th>RS-232</th> <th>RS-422</th> <th>RS-485-4w</th> <th>RS-485-2w</th> </tr> </thead> <tbody> <tr><td>2</td><td>TxD</td><td>RxD+(B)</td><td>RxD+(B)</td><td>Data+(B)</td></tr> <tr><td>3</td><td>RxD</td><td>TxD+(B)</td><td>TxD+(B)</td><td>-</td></tr> <tr><td>4</td><td>RTS</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>5</td><td>CTS</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>6</td><td>DSR</td><td>-</td><td>-</td><td>-</td></tr> <tr><td>7</td><td>GND</td><td>GND</td><td>GND</td><td>GND</td></tr> <tr><td>8</td><td>DCD</td><td>TxD-(A)</td><td>TxD-(A)</td><td>-</td></tr> <tr><td>20</td><td>DTR</td><td>RxD-(A)</td><td>RxD-(A)</td><td>Data-(A)</td></tr> <tr><td>22</td><td>-</td><td>-</td><td>-</td><td>-</td></tr> </tbody> </table>	PIN	RS-232	RS-422	RS-485-4w	RS-485-2w	2	TxD	RxD+(B)	RxD+(B)	Data+(B)	3	RxD	TxD+(B)	TxD+(B)	-	4	RTS	-	-	-	5	CTS	-	-	-	6	DSR	-	-	-	7	GND	GND	GND	GND	8	DCD	TxD-(A)	TxD-(A)	-	20	DTR	RxD-(A)	RxD-(A)	Data-(A)	22	-	-	-	-
PIN	RS-232	RS-422	RS-485-4w	RS-485-2w																																																																																																		
1	DCD	TxD-(A)	TxD-(A)	-																																																																																																		
2	RxD	TxD+(B)	TxD+(B)	-																																																																																																		
3	TxD	RxD+(B)	RxD+(B)	Data+(B)																																																																																																		
4	DTR	RxD-(A)	RxD-(A)	Data-(A)																																																																																																		
5	GND	GND	GND	GND																																																																																																		
6	DSR	-	-	-																																																																																																		
7	RTS	-	-	-																																																																																																		
8	CTS	-	-	-																																																																																																		
9	-	-	-	-																																																																																																		
PIN	RS-232	RS-422	RS-485-4w	RS-485-2w																																																																																																		
2	TxD	RxD+(B)	RxD+(B)	Data+(B)																																																																																																		
3	RxD	TxD+(B)	TxD+(B)	-																																																																																																		
4	RTS	-	-	-																																																																																																		
5	CTS	-	-	-																																																																																																		
6	DSR	-	-	-																																																																																																		
7	GND	GND	GND	GND																																																																																																		
8	DCD	TxD-(A)	TxD-(A)	-																																																																																																		
20	DTR	RxD-(A)	RxD-(A)	Data-(A)																																																																																																		
22	-	-	-	-																																																																																																		
描述	DB44 male to DB9 male x4	DB44 male to DB25 male x4																																																																																																				
电缆长度	50 cm																																																																																																					
相关产品	详情请看A-2																																																																																																					

8针RJ45转DB9/DB25连接线

配件名	CBL-RJ45F25-150	CBL-RJ45F9-150	CBL-RJ45M25-150	CBL-RJ45M9-150	CBL-RJ45SF25-150	CBL-RJ45SF9-150	CBL-RJ45SM25-150	CBL-RJ45SM9-150
配件图像								
针脚分配								
电缆类型	-	-	-	-	Shielded			
主板端	8-pin RJ45 x 1							
设备端	DB25 female x 1	DB9 female x 1	DB25 male x 1	DB9 male x 1	DB25 female x 1	DB9 female x 1	DB25 male x 1	DB9 male x 1
电缆长度	150 cm							
相关产品	CP-104JU, OPT8-RJ45, NPort 5210, NPort 5600, NPort 6600, CN2510/2600, NPort W2004, UC-7410/7420							

A

配件 > 串口连接配件

10针RJ45转DB9/DB25连接线

配件名	CN20030	CN20040	CN20060	CN20070
配件图像				
针脚分配				
主板端	10-pin RJ45 x 1			
设备端	DB25 female x 1	DB25 male x 1	DB9 male x 1	DB9 female x 1
电缆长度	150 cm			
相关产品	C320Turbo Series, CP-204J, CI-104J, A52, A53, A60			

布线工具

配件名	TB-M9	TB-F9	TB-M25	TB-F25	ADP-RJ458P-DB9M	ADP-RJ458P-DB9F
配件图像						
类型	DB9 male DIN-Rail wiring terminal	DB9 female DIN-Rail wiring terminal	DM25 male DIN-Rail wiring terminal	DB25 female DIN-Rail wiring terminal	RJ45-to-DB9 adaptor (male)	RJ45-to-DB9 adaptor (female)
接口	DB9 male	DB9 female	DB25 male	DB25 female	-	-
额定电压	300 V, 20 A (IEC250V 10A)					
工作温度	-40 ~105°C (-40 ~221°F)					
适用电缆	24-12 AWG (IEC 0.5-2.5 mm ²)					
尺寸	77.5 x 45 x 51 mm (3.05 x 1.77 x 2.01 in)		77.5 x 90 x 51 mm (3.05 x 3.54 x 2.01 in)			

A

配件 > 串口连接配件

电源配件

电源线

配件名	PWC-C13US-3B-183	PWC-C-13EU-3B-183 (CEE 7/7 to IEC C13)	PWC-C13UK-3B-183	PWC-C13JP-3B-183	PWC-C13AU-3B-183	PWC-C13CN-3B-183
配件图像						
适用区域	US	EU	UK	JP	AU	CN
电压	125 V	250 V	250 V	125 V	250 V	250 V
线径	6.3 ± 0.2 mm	6.7 ± 0.2 mm	6.7 ± 0.2 mm	7.0 ± 0.2 mm	6.7 ± 0.2 mm	6.7 ± 0.2 mm
最大电流	10 A	10 A	10 A	7 A	10 A	10 A
长度	1830 ± 30 mm	1830 ± 30 mm	1830 ± 30 mm	1830 ± 30 mm	1830 ± 30 mm	1830 ± 30 mm
相关产品	CN2500 Series, NPort 6600 Series, NPort 5600 Series, PWR-12200-DT-S1					

配件名	PWC-C7US-2B-183	PWC-C7EU-2B-183	PWC-C7UK-2B-183	PWC-C7JP-2B-183	PWC-C7AU-2B-183	PWC-C7CN-2B-183
配件图像						
适用区域	US	EU	UK	JP	AU	CN
长度	1830 ± 200 mm	1830 ± 200 mm	1830 ± 200 mm	1830 ± 200 mm	1830 ± 200 mm	1830 ± 200 mm
相关产品	PWR-12125-DT-S2					

电源适配器

配件名	PWR-12050-WPUSJP-S1	PWR-12050-WPEU-S1	PWR-12050-WPUK-S1	PWR-12050-WPAU-S1	PWR-12050-WPCN-S1
配件图像					
输入范围	100-240VAC 50-60Hz				
I/P	100-240VAC 50-60Hz				
输入插头	US/JP				
插头类型	EU				
输出范围	0.5A @ 12VDC				
O/P	0.5A @ 12VDC				
输出插头	S-Type 5.5/2.1/7.5				
连接类型	S-Type 5.5/2.1/7.5				
外径	5.5 ± 0.1 mm				
内径	2.1 ± 0.1 mm				
机械特性	尺寸 (L x W x H)				
尺寸 (L x W x H)	64 x 40.5 x 47.5 mm	64 x 40.5 x 68.7 mm	64 x 40.5 x 56.2 mm	64 x 40.5 x 58.5 mm	64 x 40.5 x 46.5 mm
重量	70g	70g	70g	70g	70g
长度	1530 ± 100 mm	1530 ± 100 mm	1530 ± 100 mm	1530 ± 100 mm	1530 ± 100 mm
工作环境	工作温度				
工作温度	0 ~ 40°C (32 ~ 104°F)				
安规认证	Safety				
Safety	CE/FCC/UL/GS/PSE/RCM/OCC				
相关产品	NPort 5110A, NPort 5130A, NPort 5150A, NPort 5210A, NPort 5230A, NPort 5250A, NPort Z2150/Z3150, NPort W2150A/W2250A				

A

配件 > 电源配件

配件名	PWR-12050-WPUSJP-S2	PWR-12050-WPEU-S2	PWR-12050-WPUK-S2	PWR-12050-WPAU-S2	PWR-12050-WPCN-S2
配件图像					
输入范围	100-240VAC 50-60Hz				
I/P	100-240VAC 50-60Hz				
输入插头	100-240VAC 50-60Hz				
插头类型	US/JP	EU	UK	AU	CN
输出范围	0.5A @ 12VDC				
O/P	0.5A @ 12VDC				
输出插头	L-Type 5.5/2.1/9.0				
连接类型	L-Type 5.5/2.1/9.0				
外径	5.5 ± 0.1 mm				
内径	2.1 ± 0.1 mm				
机械特性	尺寸 (L x W x H)				
	64 x 40.5 x 47.5 mm	64 x 40.5 x 68.7 mm	64 x 40.5 x 56.2 mm	64 x 40.5 x 58.5 mm	64 x 40.5 x 46.5 mm
重量	70g				
长度	1830 ± 100 mm				
工作环境	工作温度				
	0 ~ 40°C (32 ~ 104°F)				
安规认证	Safety				
	CE/FCC/UL/RMC/PSE/CCC				
相关产品	NPort 5110, NPort 5130, NPort 5150, NPort 5210, NPort 5230, NPort 5232, NPort 5232I, MGate MB3180, MGate MB3280, DE-211, DE-311, A52, A53				

配件名	PWR-12125-USJP-S1	PWR-12150-EU-S2	PWR-12150-UK-S2	PWR-12150-AU-S2	PWR-12150-CN-S1
配件图像					
输入范围	100-240 VAC 50-60Hz				
I/P	100-240 VAC 50-60Hz				
输入插头	100-240 VAC 50-60Hz				
插头类型	US/JP	EU	UK	AU	CN
输出范围	1.25A @ 12VDC				
O/P	1.25A @ 12VDC				
输出插头	L-Type 5.5/2.1/9.5				
连接类型	L-Type 5.5/2.1/9.0				
外径	5.5 ± 0.1 mm				
内径	2.1 ± 0.1 mm				
机械特性	尺寸 (L x W x H)				
	74 x 43.5 x 52.5 mm	70 x 45 x 66.5 mm	70 x 48 x 60 mm	70 x 55 x 56 mm	70 x 45 x 54 mm
重量	108g				
长度	1530 ± 100 mm				
工作环境	工作温度				
	0 ~ 40°C (32 ~ 104°F)				
安规认证	Safety				
	CE/FCC/UL/RMC/GS				
相关产品	NPort 5410, NPort 5430, NPort 5430I, NPort 5450, NPort 5450I, MGate MB3480				

A

配件 > 电源配件

外径	PWR-12200-DT-S1	PWR-12125-DT-S2	PWR-12150-CN-S2
配件图像			
输入范围	100-240 VAC 50-60Hz		
I/P	100-240 VAC 50-60Hz	100-240 VAC 50-60Hz	100-240 VAC 50-60Hz
输入插头	Desktop		
插头类型	Desktop	Desktop	CN
输出范围	2A @ 12VDC		
O/P	2A @ 12VDC	1.25A @ 12VDC	1.5A @ 12VDC
输出插头	S-Type 5.5/2.1/7.5		
连接类型	S-Type 5.5/2.1/7.5	S-Type 5.5/2.1/7.5	S-Type 5.5/2.1/7.5
外径	5.5 ± 0.1 mm	5.5 ± 0.1 mm	5.5 ± 0.1mm
内径	2.1 ± 0.1 mm	2.1 ± 0.1 mm	2.1 ± 0.1mm
机械特性	尺寸 (L x W x H)		
	110.8 x 51.8 x 32 mm	75 x 47.5 x 27.3 mm	70 x 45 x 54mm
重量	200g	200g	200g
长度	1800 ± 200 mm	1530 ± 100 mm	1800 ± 200 mm
工作环境	工作温度		
	0 ~ 40°C (32 ~ 104°F)	0 ~ 40°C (32 ~ 104°F)	0 ~ 40°C (32 ~ 104°F)
安规认证	Safety		
	UL/CE/FCC/GS/CCC/PSE/BSMI/TUV	UL/GS/CE/FCC/PSE	CCC
相关产品	NPort 5610-8-DT, NPort 5610-8-DT-J, NPort 5650-8-DT, NPort 5650-8-DT-J, NPort 5650I-8-DT, NPort 5610-8-DTL, NPort 5650I-8-DTL, NPort 5650I-DTL		
	NPort 6150, NPort 6250-M-SC, NPort 6250, NPort 6250-S-SC, NPort 6450, UPort 1250I, UPort 1450, UPort 1450I, UPort 1610-8, UPort 1650-8		NPort 6150, NPort 6250, NPort 6250-M-SC, NPort 6250-S-SC, NPort 6450, UPort 1250I, UPort 1450, UPort 1450I, UPort 1610-8, UPort 1650-8

注意：PWR-12200-DT-S1和PWR-12125-DT-S2不包括电源线


配件名	PWR-12300-WPUSJP-S1	PWR-12300-WPEU-S1	PWR-12300-WPUK-S1	PWR-12300-WPAU-S1	PWR-12300-WPCN-S1
配件图像					
输入范围	100-240 VAC 50-60Hz				
I/P	100-240 VAC 50-60Hz	100-240 VAC 50-60Hz	100-240 VAC 50-60Hz	100-240 VAC 50-60Hz	100-240 VAC 50-60Hz
输入插头	US/JP				
插头类型	US/JP	EU	UK	AU	CN
输出范围	3A @ 12VDC				
O/P	3A @ 12VDC	3A @ 12VDC	3A @ 12VDC	3A @ 12VDC	3A @ 12VDC
输出插头	S-Type 5.5/2.1/7.5				
连接类型	S-Type 5.5/2.1/7.5	S-Type 5.5/2.1/7.5	S-Type 5.5/2.1/7.5	S-Type 5.5/2.1/7.5	S-Type 5.5/2.1/7.5
外径	5.5 ± 0.1 mm	5.5 ± 0.1 mm	5.5 ± 0.1 mm	5.5 ± 0.1 mm	5.5 ± 0.1 mm
内径	2.1 ± 0.1 mm	2.1 ± 0.1 mm	2.1 ± 0.1 mm	2.1 ± 0.1 mm	2.1 ± 0.1 mm
机械特性	尺寸 (L x W x H)				
	74 x 43.5 x 52.3 mm	74 x 43.5 x 73.5 mm	74 x 43.5 x 61 mm	74 x 43.5 x 63.3 mm	74 x 43.5 x 51.3 mm
重量	163g	163g	163g	163g	163g
长度	1530 ± 200 mm	1530 ± 200 mm	1530 ± 200 mm	1530 ± 200 mm	1530 ± 200 mm
工作环境	工作温度				
	0 ~ 40° C (32 ~ 104°F)	0 ~ 40°C (32 ~ 104°F)	0 ~ 40°C (32 ~ 104°F)	0 ~ 40°C (32 ~ 104°F)	0 ~ 40°C (32 ~ 104°F)
安规认证	Safety				
	FCC/CE/UL/GS/CCC/RCM/PSE	FCC/CE/UL/GS/CCC/RCM/PSE	FCC/CE/UL/GS/CCC/RCM/PSE	FCC/CE/UL/GS/CCC/RCM/PSE	FCC/CE/UL/GS/CCC/RCM/PSE
相关产品	UPort 204, UPort 207, UPort 404, UPort 407				

宽温电源适配器

配件名	PWR-12150-USJP-SA-T	PWR-12150-EU-SA-T	PWR-12150-UK-SA-T	PWR-12150-AU-SA-T	PWR-12150-CN-SA-T
配件图像					
输入范围	100-240 VAC, 50-60 Hz				
I/P	100-240 VAC, 50-60 Hz				
输入插头					
插头类型	US/JP	EU	UK	AU	CN
输出范围	1.5A @ 12VDC				
O/P	1.5A @ 12VDC				
保护要求	Over current protection/ Over voltage protection				
保护	Over current protection/ Over voltage protection				
输出插头					
连接类型	L-Type 5.5/2.1/7.5	L-Type 5.5/2.1/7.5	L-Type 5.5/2.1/7.5	L-Type 5.5/2.1/7.5	L-Type 5.5/2.1/7.5
外径	5.5 ± 0.1 mm	5.5 ± 0.1 mm	5.5 ± 0.1 mm	5.5 ± 0.1 mm	5.5 ± 0.1 mm
内径	2.1 ± 0.1 mm	2.1 ± 0.1 mm	2.1 ± 0.1 mm	2.1 ± 0.1 mm	2.1 ± 0.1 mm
机械特性					
尺寸 (L x W x H)	32 x 70.3 x 88 mm	32 x 85.3 x 88 mm	50 x 91 x 82.5 mm	41 x 73.9 x 89.5 mm	32 x 69 x 88 mm
重量	200g	200g	200g	200g	200g
长度	1500 ± 200 mm	1500 ± 200 mm	1500 ± 200 mm	1500 ± 200 mm	1500 ± 200 mm
工作环境					
工作温度	-40 ~ 75°C (-40 ~ 167°F)	-40 ~ 75°C (-40 ~ 167°F)	-40 ~ 75°C (-40 ~ 167°F)	-40 ~ 75°C (-40 ~ 167°F)	-40 ~ 75°C (-40 ~ 167°F)
安规认证					
Safety	FCC/UL/PSE	TUV/CE/GS	CE	RCM	CCC
相关产品	NPort 5110-T, NPort 5450-T, NPort 5450I-T, NPort 5110A-T, NPort 5610-8-DTL-T, NPort 5650-8-DTL-T, NPort 5650I-8-DTL-T, NPort 5130A-T, NPort 5150A-T, NPort 5210A-T, NPort 5230A-T, NPort 5250A-T, NPort 6100-T, NPort 6200-T, NPort 6400-T				

电源适配器

24/48 VDC电源适配器，支持导轨安装

	24 VDC DIN-Rail Power Supplies					48 VDC DIN-Rail Power Supplies		
配件名	DR-45-24	DR-75-24	DR-120-24	MDR-40-24	MDR-60-24	DR-75-48	DR-120-48	DRP-240-48
配件图像								
机械特性和工作环境								
尺寸 (mm)	78 x 67 x 93	55.5 x 100 x 125.2	65.5 x 100 x 125.2	40 x 90 x 100	40 x 90 x 100	55.5 x 100 x 125.2	65.5 x 100 x 125.2	125.5 x 125.5 x 100
重量	400 g	550 g	650 g	260 g	280 g	550 g	650 g	1.2 kg
工作温度	-10 ~ 50°C (14 ~ 122°F)	-10 ~ 60°C (14 ~ 140°F)		-20 ~ 70°C (-4 ~ 158°F)		-10 ~ 60°C (14 ~ 140°F)		-10 ~ 70°C (14 ~ 158°F)
相对湿度	20 ~ 90% RH	20 ~ 90% RH		20 ~ 90% RH		20 ~ 90% RH		
电源要求								
电源功耗	45 W	75 W	120 W	40 W	60 W	75 W	120 W	240 W
输入电压	85-264 VAC (47-63 Hz), or 120-370 VDC		88-132 VAC, or 176-264 VAC (47-63 Hz) by switch, or 248-370 VDC	85-264 VAC (47-63 Hz) or 120-370 VDC		85-264 VAC (27-63 Hz) or 120-370 VDC	88-132 VAC, or 176-264 VAC (47-63 Hz) by switch, or 248-370 VDC	85-264 VAC (47-63 Hz) or 120-370 VDC
输出电压	48 W (24 VDC @ 0-2 A)	76.8 W (24 VDC @ 0-3.2 A)	120 W (24 VDC @ 0-5 A)	40 W (24 VDC @ 0-1.7 A)	60 W (24 VDC @ 0-2.5 A)	76.8 W (48 VDC @ 0-1.6 A)	120 W (48 VDC @ 0-2.5 A)	240 W (48 VDC @ 0-5 A)
过压保护	27.6-32.4 V	29-33 V		31.2-36 V		58-65 V		54-60 V
过载保护	105-150%							
类型	Constant Current Limiting							
重启	Auto Recovery							
浪涌电源	30 A and 115 V, or 60 A and 230 V							
可靠性								
Safety	EN 60950-1, UL 508 approved							
EMC	EN 55022 Class B, EN 61000-4-2/3/4/5/6/8/11, ENV 50204, EN 61000-3-2, EN 50082-2							
保修期	3 years (see www.moxa.com/warranty)							

A

配件 > 电源配件

光纤配件

光纤配件

SC针式到ST孔式全双工适配器



SC针式转ST孔式全双工适配器是一种可选配件，为Moxa工业以太网交换机用户提供更多的光纤连接方式。只需在任何一款Moxa工业以太网交换机的SC接口处插上这款适配器，就可以将SC接头转为ST接头。这样您就可以在Moxa任何一款工业以太网交换机上使用ST接头，而无需额外跳线。

A

配件 > 光纤配件

ADP-SCm-STf-S

SC针式到ST孔式单模光纤全双工适配器

单模: 9/125 μm
 金属环扣管: Zirconia Ceramic
 产品颜色: Blue
 插入损失: 0.5/1.1 (TYP/MAX)
 SC端: SC male
 ST端: ST female

ADP-SCm-STf-M

SC针式到ST孔式多模光纤全双工适配器

多模: 62.5/125 μm
 金属环扣管: Zirconia Ceramic
 产品颜色: Gray
 插入损失: 0.1/0.3 (TYP/MAX)
 SC端: SC male
 ST端: ST female

金属帽

配件名	A-CAP-M12M-M	A-CAP-M12F-M	A-CAP-N-M	A-CAP-M30M-MIP67	A-CAP-WPRJ45-MC
配件图像					
配件描述	Metal cap to cover M12-male connector	Metal cap to cover M12-female connector	Metal cap to cover N-type connector	Metal cap to cover M30 connector	Metal cap with chain for RJ45 connector
相关产品	Power cap for the AWK-4121 AWK-4131-M12 AWK-6222 AWK-6232-M12 DI/O cap for the AWK-4131-M12 AWK-6232-M12 PM-7200-4M12 TN Series	DI/O cap for the AWK-4121 AWK-6222 LAN cap for the AWK-1121, AWK-1127 AWK-3121-M12 AWK-3131-M12 AWK-4131-M12 AWK-5222-M12 AWK-5232-M12 AWK-6232-M12 TN Series	Antenna cap for the AWK-4121 AWK-4131-M12 AWK-6222 AWK-6232-M12	SFP cap for the AWK-4131-M12	Console & LAN caps for the AWK-4121 AWK-6222 Console cap for the AWK-4131-M12 AWK-6232-M12

连接器

配件名	CBL-M12(FF5P)/ OPEN-100 IP67	CBL- M12D(MM4P)/ RJ45-100 IP67	CBL-M23(FF6P)/ OPEN-BK-100 IP67	M12A-5P-IP68	M12A-8PMM- IP68	CBL- M12DFF4PRJ45- BK-10-IP67	CBL- M12MM8PRJ45- BK-100-IP67	M12A-8PFF-IP67	
配件图像									
配件描述	1-meter M12-to-5-pin power cable with IP67-rated 5-pin female A-coded M12 connector	1-meter M12-to-RJ45 Cat-5C UTP Ethernet cable with IP67-rated 4-pin male D-coded M12 connector	1-meter M23-to-6-pin power cable with IP-67-rated female 6-pin M23 connector	Field-installation A-coded M12 screw-in 5-pin connector, female connector female pins	Field-installation A-coded M12 screw-in 8-pin connector, male connector male PIN	M12-to-RJ45 Cat-5E UTP Ethernet cable with IP67-rated female 4-pin D-coded M12 connector	M12-to-RJ45 Cat-5E UTP Ethernet cable with IP67-rated male 8-pin A-coded M12 connector	Field-installation A-coded M12 screw-in 8-pin connector, female connector female PIN	
电缆长度	1 m	-	-	-	-	10 m	1 m	-	
相关产品	AWK-4121 AWK-4131-M12 AWK-6222 AWK-6232-M12	TN Series	TN Series	Power connector for the AWK-4121 Series AWK-4131-M12 AWK-6222 Series AWK-6232-M12	DI/O connector for the AWK-4121 AWK-6222 LAN connector for the AWK-4131-M12 AWK-6232-M12	AWK-4121 AWK-6222	AWK-4131 Series	DI/DO connector for the AWK-4131 Series AWK-6232-M12	

现场安装接头	
配件名	A-PLG-WPM30IP67-01 A-PLG-WPRJ
配件图像	
配件描述	Field-Installation for M30 plug Field-installation RJ-type plug
电缆长度	- -
相关产品	SFP LAN connector for the AWK-4131-M12 LAN connector for the AWK-4121 AWK-6222

A

配件 > 连接器






安装工具

A

配件 > 安装工具

壁挂安装工具				
配件名	WK-30	WK-32	WK-36-02	WK-46
配件图像				
尺寸	40 x 30 x 1 mm	30.3 x 140 x 12.3 mm	36 x 67 x 2 mm	51.6 x 66.8 x 1 mm
相关产品	EDS-205A 系列 EDS-G205 系列 EDS-G205A-4PoE 系列 ICF-11701 系列	EDS-828 系列 EDS-728 系列	NPort IA5150A 系列 NPort IA5250A 系列	EDS-208A 系列 EDS-300 系列 EDS-400A 系列 EDS-500A 系列 EDS-G308 系列 EDS-G509 系列 EDS-P206A-4PoE 系列 EDS-P308 系列 EDS-P510 系列 OBU-102 系列 IMC-101G/101 系列 ioLogik W5312 系列 ioLogik W5340 系列 PT-500 系列 VPort 254 系列 VPort 351 系列 VPort 354 系列 VPort 364 系列 VPort 451 系列 VPort 461 系列 VPort 3310 系列 VPort D351 VPort D361 系列

壁挂安装工具					
配件名	WK-51-01	WK-55	WK-75	WK-90	WK-195
配件图像					
尺寸	55 x 67 x 1 mm	55 x 34.5 x 2.5 mm	75 x 90 x 2.5 mm	99 x 62 x 2.5 mm	195 x 17.5 x 52.5 mm
相关产品	AWK-1121 AWK-1127 AWK-3121 系列 AWK-3131 系列 AWK-5222 系列 EDR-G902 系列 EDR-G903 系列 EDS-P506A-4PoE 系列 EDS-316 系列 IMC-P101 系列 PTC-101 系列 NPort IA5450A 系列	AWK-4121 AWK-4131-M12 AWK-6222 AWK-6232-M12	EDS-600 系列 ioPAC 8000 系列	ioLogik E1500 系列	PT-7710 系列

导轨安装工具					Pole Mounting Kit
配件名	DK-DC50131	DK-TN-5308	DK-M12-305	DK-35A	PK-DC2DOF
配件图像					
尺寸	50 x 131 x 1 mm	66 x 174 x 12.8 mm	60 x 125 x 12.8 mm	42.5 x 10 x 19.34 mm	-
相关产品	TN-5500 系列 AWK-3121 系列 AWK-3131 系列 AWK-4121 系列 AWK-4131 系列 AWK-5222 系列 AWK-6222 系列 AWK-6232 系列 ioPAC 8000 系列 ioLogik E1500 系列 MxNVR-MO4 系列	TN-5308 系列	TN-5305 系列	MGate™ 3x80 系列 NPort Express DE-211 NPort Express DE-311 NPort 5100 系列 NPort 5100A 系列 NPort 5200 系列 NPort 5200A 系列 NPort 5400 系列 NPort 6150/6250/6450 NPort W2x50A UPort 1150I UPort 404/407 UPort 1250/1250I TCF-142 系列 TCC-100/100I TCC-120/120I	AWK-4121 AWK-4131-M12 AWK-6222 AWK-6232-M12



简约



稳健



以用户为中心的体验

Moxa Green Core

传递统一的品牌形象

Moxa 新款 Green Core 产品识别融合了 Moxa 的企业色彩一抹特别的绿荫——旨在统一品牌形象。Green Core 设计以 Moxa “可靠的网络、真诚的服务”品牌承诺为基础，强调三个理念：简约、稳健和以用户为中心的体验。

从现在开始，所有新产品均采用 Green Core 设计，现有产品转换工作于 2014 年 5 月开始，全部转换将计划于 2015 年年末完成。欲了解有关 Moxa Green Core、Moxa 品牌承诺、Moxa 本质以及 Moxa 故事的更多详情，请访问以下网页：www.moxa.com/greencore

我们尽最大努力使本型录里的信息准确。即便如此，本型录里面的所有信息也不作为法律合同或任何承诺的依据。该型录仅供参考，Moxa 保留在任何时候更新或修改本型录中信息的权利。

最新的产品信息请登录：www.moxa.com/product